

USB 3.2 Gen 1 USB-C to DVI Adapters



Purchased product
may differ from image.

Models:

U444-06N-D-C

U444-06N-DB-C

U444-06N-DU-C

U444-06N-DUB-C

U444-06N-DGU-C

U444-06N-DGUB-C

USB Type-C® and
USB-C® are registered
trademarks of USB
Implementers Forum.

Este manual está disponible en español en la página de
Eaton: Tripplite.Eaton.com/support

Ce manuel est disponible en français sur le site Web de
Eaton : Tripplite.Eaton.com/support

Dieses Handbuch ist in deutscher Sprache auf der Eaton-
Website verfügbar: Tripplite.Eaton.com/support

Questo manuale è disponibile in italiano sul sito web di
Eaton: Tripplite.Eaton.com/support

EATON

Powering Business Worldwide

Package Includes

- U444-06N-D-C (White), U444-06N-DB-C (Black), U444-06N-DU-C (White), U444-06N-DUB-C (Black), U444-06N-DGU-C (White) or U444-06N-DGUB-C (Black)
- Owner's Manual

Optional Accessories

- P561-Series DVI Single Link Cables
- U322-Series USB 3.2 Gen 1 A/B Device Cables
- U326-Series USB 3.2 Gen 1 Micro-B Device Cables
- N201-Series Cat6 Gigabit Snagless Patch Cables
- U420-003 USB 3.2 Gen 1 USB-C Male/Male Cable – 3 ft.

Product Features

Note: This section lists features for all of the USB Type-C models referenced in this manual. See the **USB Type-C Features** chart to determine which features your model supports.

- Supports USB DisplayPort Alternate Mode for connecting a DVI monitor via a USB-C port
- Supports DVI Single Link video resolutions up to 1920 x 1080/1080p @ 60 Hz
- Supports DVI digital transfer rates of 6.75 Gbps (2.25 Gbps per channel)

Product Features

- Ethernet port supports true 10/100/1000 Mbps network speeds
- USB-A hub port supports data transfer rates up to 5 Gbps; backward compatible with previous USB generations
- USB-C charging port for charging your device
- USB-C port supports power input up to 20V 3A (60W)
- Plug and play; no software or drivers required

USB Type-C Features

Models	U444-06N-D-C	U444-06N-DB-C	U444-06N-DU-C	U444-06N-DUB-C	U444-06N-DGU-C	U444-06N-DGUB-C
DVI Port	Y	Y	Y	Y	Y	Y
USB-A Hub Port	N	N	Y	Y	Y	Y
Gigabit Ethernet Port	N	N	N	N	Y	Y
USB-C Charging Port	Y	Y	Y	Y	Y	Y

Installation

Note: When the unit is connected to the USB-C port on your computer and to a network via Cat5e/6 cabling, a network connection will be automatically established. If no connection is made, you can manually establish one by going to your computer's network settings page. For example, on a Mac you would navigate to the Network section found in System Preferences, click the 'Assist Me' button to get to the Network Setup Assistant, then follow the prompts to establish a connection.

1. Connect the adapter's USB Type-C connector to the USB-C port on your laptop, tablet or other device.
2. Connect the adapter's DVI port to the DVI port on a monitor using a DVI cable (such as P561-Series DVI cables).
3. Charge your device by connecting its USB-C to the USB-C port on the adapter.
4. Connect a USB device to the adapter's USB-A hub port.*
5. Connect the adapter's RJ45 port to a network using a UTP cable (such as N201-Series Cat6 cables.)*

*See the **USB Type-C Features** chart for the features your product supports.

Specifications

Models	U444-06N-D-C	U444-06N-DB-C	U444-06N-DU-C	U444-06N-DUB-C	U444-06N-DGU-C	U444-06N-DGUB-C
Connectors—Input						
USB	USB-C (Male)					
Charging	USB-C (Female)					
Connectors—Output						
DVI	DVI (Female)					
USB	N/A	USB-A (Female)				
Ethernet	N/A				RJ45 (Female)	
Environmental						
Operating Temperature	32° to 113°F (0° to 45°C)					
Operating Humidity	10% to 85% RH, Non-Condensing					
Storage Temperature	14° to 158°F (-10° to 70°C)					
Storage Humidity	5% to 90% RH, Non-Condensing					
Power Requirements						
USB-C Charging Port	Supports up to 20V 3A (60W) Input					
USB 3.2 Gen 1 Port	N/A	Provides up to 5V 1A (5W) Output				

Warranty

3-YEAR LIMITED WARRANTY

We warrant our products to be free from defects in materials and workmanship for a period of three (3) years from the date of initial purchase. Our obligation under this warranty is limited to repairing or replacing (at its sole option) any such defective products. Visit Triplite.Eaton.com/support/product-returns before sending any equipment back for repair. This warranty does not apply to equipment which has been damaged by accident, negligence or misapplication or has been altered or modified in any way.

EXCEPT AS PROVIDED HEREIN, WE MAKE NO WARRANTIES, EXPRESS OR IMPLIED, INCLUDING WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. Some states do not permit limitation or exclusion of implied warranties; therefore, the aforesaid limitation(s) or exclusion(s) may not apply to the purchaser.

EXCEPT AS PROVIDED ABOVE, IN NO EVENT WILL WE BE LIABLE FOR DIRECT, INDIRECT, SPECIAL, INCIDENTAL OR CONSEQUENTIAL DAMAGES ARISING OUT OF THE USE OF THIS PRODUCT, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE. Specifically, we are not liable for any costs, such as lost profits or revenue, loss of equipment, loss of use of equipment, loss of software, loss of data, costs of substitutes, claims by third parties, or otherwise.

Warranty

FCC Notice, Class B

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Any changes or modifications to this equipment not expressly approved by Eaton could void the user's authority to operate this equipment.

Warranty

WEEE Compliance Information for Customers and Recyclers (European Union)



Under the Waste Electrical and Electronic Equipment (WEEE) Directive and implementing regulations, when customers buy new electrical and electronic equipment from Eaton, they are entitled to:

- Send old equipment for recycling on a one-for-one, like-for-like basis (this varies depending on the country)
- Send the new equipment back for recycling when this ultimately becomes waste

Use of this equipment in life support applications where failure of this equipment can reasonably be expected to cause the failure of the life support equipment or to significantly affect its safety or effectiveness is not recommended.

Eaton has a policy of continuous improvement. Specifications are subject to change without notice.



Eaton
1000 Eaton Boulevard
Cleveland, OH 44122
United States
Eaton.com

© 2023 Eaton
All Rights Reserved
Publication No.
23-10-202 /
93-357A_RevE
December 2023



Eaton is a registered trademark.

All trademarks are property of their respective owners.