

Owner's Manual

4K x 2K HDMI Audio De-Embedder / Extractor with HDCP 2.2

Model: P130-000-AUD4K6

Este manual esta disponible en español en la página de Tripp Lite:
www.tripplite.com

Ce manuel est disponible en français sur le site Web de Tripp Lite :
www.tripplite.com

Русскоязычная версия настоящего руководства представлена на
веб-сайте компании Tripp Lite по адресу: www.tripplite.com

PROTECT YOUR INVESTMENT!

Register your product for quicker service and ultimate peace of mind.
You could also win an ISOBAR6ULTRA surge protector—a \$100 value!
www.tripplite.com/warranty



1111 W. 35th Street, Chicago, IL 60609 USA • www.tripplite.com/support

Copyright © 2018 Tripp Lite. All rights reserved.

Package Includes

- P130-000-AUD4K6
- USB Micro-B Cable, 3 ft.
- Owner's Manual

Optional Accessories

- A060-Series RCA Digital Coaxial Audio Cables
- A102-Series TOSLINK Digital Audio Cables
- P312-Series 3.5 mm Mini Stereo Audio Cables
- P569-Series High Speed HDMI Cables
- U280-W01-QC3 Single-Port USB Wall Charger

Product Features

- Extracts audio from an HDMI signal for use on a separate audio system
- Transmits Ultra High Definition (UHD) video resolutions up to 3840 x 2160 @ 60 Hz
- Supports stereo and 7.1 surround sound audio
- Supports HDMI 2.0 and HDCP 2.2 specifications
- Features 3.5 mm stereo, TOSLINK and RCA coaxial audio outputs
- Supports LPCM uncompressed audio, and DTS and Dolby Digital compressed audio
- Supports up to 24-bit True Color (8 bits per channel) at 4K, and up to 36-bit Deep Color (12-bits per channel) at 1080p
- Supports optional 3D formats up to 60 Hz
- Bus-powered via Micro USB-B port; no external power supply needed
- Plug-and-play; no drivers or software needed

Installation

Notes:

- *Make sure all devices you are connecting are powered off prior to installation.*
 - *If the 3.5 mm port is in use, you will need to enable the stereo audio function by adjusting the source's audio output setting to "PCM" instead of "Auto".*
- 1.** Connect the HDMI source to the unit's HDMI input using an HDMI audio/video cable.
 - 2.** Connect an HDMI monitor to the unit's HDMI output port using a second HDMI audio/video cable.
 - 3.** Connect the unit to a set of speakers, an audio receiver or other audio system equipped with 3.5 mm mini-stereo, TOSLINK, or RCA digital outputs.
 - 4.** Use the included USB Micro-B cable to connect the unit to a USB port on the display or a USB wall charger. The unit's green power LED will illuminate to indicate it is receiving power.
 - 5.** Power on the connected devices. The orange LED will indicate the unit is transmitting audio and video from the source to the display and audio system.

Specifications

Specification	Value
Input Port	HDMI (Female), USB Micro-B (Female) for power
Output Ports	HDMI (Female), TOSLINK (Female), RCA Coaxial (Female), 3.5 mm Mini-Stereo (Female)
Operating Temperature	32 to 104°F (0 to 40°C)
Storage Temperature	5 to 122°F (-15 to 50°C)
Relative Humidity	0 to 85%, Non-Condensing
External Power Supply	USB
Power Consumption	2.95W
Max Video Resolutions	3840 x 2160 @ 60 Hz
Unit Dimension (H x W x D, in.)	2.99 x 2.42 x 1
Unit Dimension (H x W x D, mm)	76 x 61.5 x 25.5
Unit Weight (lb.)	0.15
Unit Weight (kg)	0.07

Warranty and Product Registration

2-YEAR LIMITED WARRANTY

TRIPP LITE warrants its products to be free from defects in materials and workmanship for a period of two (2) years from the date of initial purchase. TRIPP LITE's obligation under this warranty is limited to repairing or replacing (at its sole option) any such defective products. To obtain service under this warranty, you must obtain a Returned Material Authorization (RMA) number from TRIPP LITE or an authorized TRIPP LITE service center. Products must be returned to TRIPP LITE or an authorized TRIPP LITE service center with transportation charges prepaid and must be accompanied by a brief description of the problem encountered and proof of date and place of purchase. This warranty does not apply to equipment, which has been damaged by accident, negligence or misapplication or has been altered or modified in any way.

EXCEPT AS PROVIDED HEREIN, TRIPP LITE MAKES NO WARRANTIES, EXPRESS OR IMPLIED, INCLUDING WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE.

Some states do not permit limitation or exclusion of implied warranties; therefore, the aforesaid limitation(s) or exclusion(s) may not apply to the purchaser.

EXCEPT AS PROVIDED ABOVE, IN NO EVENT WILL TRIPP LITE BE LIABLE FOR DIRECT, INDIRECT, SPECIAL, INCIDENTAL OR CONSEQUENTIAL DAMAGES ARISING OUT OF THE USE OF THIS PRODUCT, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

Specifically, TRIPP LITE is not liable for any costs, such as lost profits or revenue, loss of equipment, loss of use of equipment, loss of software, loss of data, costs of substitutes, claims by third parties, or otherwise.

PRODUCT REGISTRATION

Visit www.triplite.com/warranty today to register your new Tripp Lite product. You'll be automatically entered into a drawing for a chance to win a FREE Tripp Lite product!*

* No purchase necessary. Void where prohibited. Some restrictions apply. See website for details.

Warranty and Product Registration

FCC Notice, Class B

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Any changes or modifications to this equipment not expressly approved by Tripp Lite could void the user's authority to operate this equipment.

WEEE Compliance Information for Tripp Lite Customers and Recyclers (European Union)



Under the Waste Electrical and Electronic Equipment (WEEE) Directive and implementing regulations, when customers buy new electrical and electronic equipment from Tripp Lite they are entitled to:

- Send old equipment for recycling on a one-for-one, like-for-like basis (this varies depending on the country)
- Send the new equipment back for recycling when this ultimately becomes waste

Use of this equipment in life support applications where failure of this equipment can reasonably be expected to cause the failure of the life support equipment or to significantly affect its safety or effectiveness is not recommended.

Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice.



Manufacturing
Excellence.

1111 W. 35th Street, Chicago, IL 60609 USA • www.tripplite.com/support