

Owner's Manual

10,050mAh 3-Port Mobile Power Bank, USB-IF Certified

Model: UPB-10K0-2U1C

USB Type-C and USB-C are trademarks of USB Implementers Forum

Este manual esta disponible en español en la página de Tripp Lite:
tripplite.com/support

Ce manuel est disponible en français sur le site Web de Tripp Lite :
tripplite.com/support

Русскоязычная версия настоящего руководства представлена на
веб-сайте компании Tripp Lite по адресу: tripplite.com/support

WARRANTY REGISTRATION

Register your product today and be automatically entered to win an
ISOBAR surge protector in our monthly drawing!

tripplite.com/warranty



1111 W. 35th Street, Chicago, IL 60609 USA • tripplite.com/support

Copyright © 2019 Tripp Lite. All rights reserved.

General Safety Instructions

- Make sure the power bank is fully charged prior to use.
- Use a cable suitable for your device when charging from the power bank.
- When charging the power bank, it is recommended you use the included USB Type-C cable.
- Under condition of low battery, the LEDs will turn off while charging a device. Recharge the power bank as soon as possible to avoid shortening the battery life.
- The battery should be charged at least every three months to avoid shortening the battery life.
- It is recommended to disconnect the charging device upon being fully charged in order to avoid further battery use.
- When the power bank enters protection mode (LEDs turn off and power bank will not charge) caused by issues such as a short circuit, use an external charger to charge the power bank so it can resume normal operation.
- Keep the power bank away from fire and avoid temperatures above 113°F (45°C) when in use and 140°F (60°C) when not in use.
- Do not expose the power bank to moisture or immerse it in water.
- Do not use a corrosive cleaner on the power bank.
- Do not squeeze or puncture the power bank. Doing so may allow electrolyte leakage of the lithium-ion battery.
- Do not attempt to disassemble, modify or fix the power bank.
- Do not use a damaged cable or power charger to charge the power bank.
- Please recycle this device at an appointed disposal location for lithium-ion batteries.

Product Features

- Simultaneously charge up to 3 phones, tablets or other mobile devices without the need for a power outlet
- USB-A and USB-C ports provide 30W maximum simultaneous charging power
- Dual USB-A ports provide 5V 2.4A (12W) of total power per port*
- USB-A ports are BC 1.2 compliant, providing up to 1.5A of fast charging power to Apple-compliant devices
- USB-C port supports PD charging up to 5V 3A (15W), 9V 2A (18W) and 12V 1.5A (18W)
- 10,050mAh capacity lets you charge at maximum power draw for hours
- Includes short circuit, overvoltage, overcurrent, overcharge and overdischarge protection for safe and reliable charging
- USB-IF certified
- Four battery power LED indicators show remaining battery capacity
- Automatic power off turns off LED indicators when not in use
- Sleek, portable design is perfect for on-the-go use

*When used simultaneously, the total power per port will be negotiated by device.

Package Includes

- UPB-10K0-2U1C
- USB-C to USB-C Cable (M/M), 3 ft. (0.9 m)
- Owner's Manual

System Requirements

- Smartphone, tablet or other mobile USB device

Optional Accessories

- M100-Series USB to Lightning Cables
- U030-Series USB 2.0 A to 5-Pin Mini-B Cables
- U038-Series USB 2.0 A to USB Type-C Cables
- U326-Series USB 3.0 A to Micro-B Cables
- U420-Series USB 3.1 Type-C M/M Cables
- U422-Series USB 3.1 Type-C to USB 3.0 Type-B Cables
- U426-Series USB 3.1 Type-C to USB 3.0 Micro-B Cables
- U428-Series USB 3.1 Type-C to USB Type-C Cables
- U280-W01-QC3-1 1-Port USB Wall Charger

Power Bank Charging Instructions

Notes:

- A power button is located on the side of the power bank. When pressed once, the LEDs will illuminate to indicate the power bank's remaining battery capacity.
- When charging the power bank, the LEDs will illuminate to indicate the battery capacity level (see table below):

LED Status	Power Bank Battery Capacity
●●●●	100%
●●●○	75% - 99%
●●○○	50% - 74%
●○○○	25%-49%
○○○○	1% - 24%

● = LED Illuminated

○ = LED Off

◎ = LED Flashing

1. Using the included USB Type-C cable, connect the In/Output USB Type-C port on the power bank to the appropriate USB port on your computer or USB charger.
2. The power bank will begin charging, with the LEDs operating per the above notes and table.

USB Device Charging Instructions

Notes:

- Before charging your devices for the first time, fully charge the power bank prior to use.
- A power button is located on the side of the power bank. When pressed once, the LEDs will illuminate to indicate the power bank's remaining battery capacity.
- When a device is connected to the USB-C port, but appears as if the charge is being used for the power bank itself, hold the power button down for 3 seconds to switch the charge from the power bank to the device.
- When charging a USB device, the LEDs will illuminate to indicate the battery capacity level (see table below):

LED Status	Power Bank Battery Capacity
●●●●	100%-75%
●●●○	74%-50%
●●○○	49% - 25%
●○○○	24% - 1%
○○○○	0

● = LED Illuminated

○ = LED Off

1. Using the included USB Type-C cable or a USB cable suitable for your device, connect your mobile devices to the USB A and/or USB-C ports on the power bank.
2. The devices will begin charging, with the LEDs operating per the above notes and table.

Specifications

USB-C Input	5V/3A (15W), 9V/2A (18W), 12V/1.5A (18W), 15V/1.2A (18W)
USB-C Output	5V/3A (15W), 9V/2A (18W), 12V/1.5A (18W)
USB-A Output	5V 2.4A (12W)
Max Output	30W
Ripple And Noise	≤200mVp-p @5V <300mVp-p @9V <300mVp-p @12V
Operating Temperature Range (Charge)	32°F to 104°F / 0°C to 40°C
Operating Temperature Range (Discharge)	32°F to 77°F / 0°C to 25°C
Storage Temperature Range	-4°F to 140°F / -20°C to 60°C
Operating Humidity Range	20 to 90% RH, Non-Condensing
Storage Humidity Range	5 to 90% RH, Non-Condensing
Color	Black
Dimensions (L x W x H)	4.9 x 2.8 x 1 in. / 124.2 x 70 x 22 mm
Weight	0.4 lb. / 200 g
Overcurrent Protection	Yes
Overvoltage Protection	Yes
Overcharge Protection	Yes
Overdischarge Protection	Yes
Short Circuit Protection	Yes
Over-Temperature Protection	Yes
Efficiency	≥ 85%

Warranty and Product Registration

1-Year Limited Warranty

TRIPP LITE warrants its products to be free from defects in materials and workmanship for a period of one (1) year from the date of initial purchase. TRIPP LITE's obligation under this warranty is limited to repairing or replacing (at its sole option) any such defective products. To obtain service under this warranty, you must obtain a Returned Material Authorization (RMA) number from TRIPP LITE or an authorized TRIPP LITE service center. Products must be returned to TRIPP LITE or an authorized TRIPP LITE service center with transportation charges prepaid and must be accompanied by a brief description of the problem encountered and proof of date and place of purchase. This warranty does not apply to equipment, which has been damaged by accident, negligence or misapplication or has been altered or modified in any way.

EXCEPT AS PROVIDED HEREIN, TRIPP LITE MAKES NO WARRANTIES, EXPRESS OR IMPLIED, INCLUDING WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE.

Some states do not permit limitation or exclusion of implied warranties; therefore, the aforesaid limitation(s) or exclusion(s) may not apply to the purchaser.

EXCEPT AS PROVIDED ABOVE, IN NO EVENT WILL TRIPP LITE BE LIABLE FOR DIRECT, INDIRECT, SPECIAL, INCIDENTAL OR CONSEQUENTIAL DAMAGES ARISING OUT OF THE USE OF THIS PRODUCT, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE. Specifically, TRIPP LITE is not liable for any costs, such as lost profits or revenue, loss of equipment, loss of use of equipment, loss of software, loss of data, costs of substitutes, claims by third parties, or otherwise.

Product Registration

Visit tripplite.com/warranty today to register your new Tripp Lite product. You'll be automatically entered into a drawing for a chance to win a FREE Tripp Lite product!*

* No purchase necessary. Void where prohibited. Some restrictions apply. See website for details.

FCC Notice, Class B

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.


Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Any changes or modifications to this equipment not expressly approved by Tripp Lite could void the user's authority to operate this equipment.

WEEE Compliance Information for Tripp Lite Customers and Recyclers (European Union)

 Under the Waste Electrical and Electronic Equipment (WEEE) Directive and implementing regulations, when customers buy new electrical and electronic equipment from Tripp Lite they are entitled to:

- Send old equipment for recycling on a one-for-one, like-for-like basis (this varies depending on the country)
- Send the new equipment back for recycling when this ultimately becomes waste

Use of this equipment in life support applications where failure of this equipment can reasonably be expected to cause the failure of the life support equipment or to significantly affect its safety or effectiveness is not recommended.

Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice.



1111 W. 35th Street, Chicago, IL 60609 USA
tripplite.com/support